

DJM-900NXS2 4-channel digital pro-DJ mixer pioneer



CARACTÉRISTIQUES

Main Features

MIDI Control

Full assignable MIDI controls

ProDJ Link

Yes

P-LOCK Fader Caps

Yes

Auto Standby

Yes

Compatible DJ Software (not included)

rekordbox dj

DVS Control

rekordbox dvs ready (not included)

Paid upgrade to Serato DJ Essentials

What's in the box

DJM-900NXS2

Power cord

USB cable

Operating Instructions (Quick Start Guide)

Specifications

Width

333 mm

Height

107.9 mm
Depth
414.2 mm
Weight
8 kg
Frequency Range
20 - 40000 Hz
Sampling Rate
96 kHz
A/D Converter
24 bit
D/A Converter
32 bit
S/N Ratio Line
105 dB
S/N Ratio Phono
88 dB
S/N Ratio Mic
79 dB
Distortion
< 0.005 % (LINE)
Channels
EQ/ISO
3 band
EQ/ISO Range
Built-in, switchable 3-band equaliser: -26 dB ~ +6 dB / 3-band isolator: $-\infty$ ~ +6 dB
Performance Control
Channels
4
Sound Color FX
Crush
Dub Echo
Filter
Noise
Sweep
Space
Beat FX
Delay
Echo
Filter
Flanger
Helix
Phaser
Ping Pong
Pitch
Slip Roll
Spiral
Reverb
Roll
Trans
Vinyl Brake
FX Frequency
Yes
X-PAD

Yes
rekordbox Quantize
Yes
Crossfader
Crossfader Type
Magvel Fader
CURVE Assignable
Yes
Fader Curve
3
Mic
Mic Connection
XLR / 1/4-inch Jack Combo
1/4-inch TRS Jack
Talkover
3 Position Switch
Talkover Attenuator
Yes
Terminals
Inputs
4 Digital (Coaxial)
4 CD/LINE (RCA)
4 PHONO (RCA)
2 MIC (XLR/TRS Jack Combo, 1/4 inch TRS Jack)
Send/Return
1 SEND (1/4-inch TS jack)
1 RETURN (1/4-inch TS jack)
LAN
1
USB
2 USB B ports
1 USB A port
Outputs
2 MASTER (XLR, RCA)
1 BOOTH (1/4 inch TRS Jack)
2 HEADPHONE MONITOR (1/4 inch Jack, mini-jack)
1 REC (RCA)
1 Digital (Coaxial)