

DJM-TOUR1 TOUR system 4-channel digital mixer with fold-out touch screen



CARACTÉRISTIQUES

Main Features

MIDI Control

Full assignable MIDI controls

ProDJ Link

Yes

P-LOCK Fader Caps

Yes

Auto Standby

Yes

DVS Control

rekordbox dvs (not included)

What's in the box

DJM-TOUR1

Power cord

USB cable

Display shade

Operating Instructions (Quick Start Guide)

Specifications

Dimensions (with fold-out display)

When upper display part is closed (W x D x H): 445.2 x 451.6 x 179.1 mm

When upper display part is upright at 90 degrees (W x D x H): 445.2 x 457.8 x 418 mm

When upper display part is fully open (W x D x H): 445.2 x 694.5 x 203.1 mm

Weight

16.1 kg

Frequency Range

20 - 40000 Hz

Sampling Rate

96 kHz

A/D Converter

24 bit

D/A Converter

32 bit

S/N Ratio Line

105 dB

S/N Ratio Phono

88 dB

S/N Ratio Mic

79 dB

Distortion

< 0.005 % (LINE)

Channels

EQ/ISO

3 band

EQ/ISO Range

Built-in, switchable 3-band equaliser: -26 dB ~ +6 dB / 3-band isolator: -∞ ~ +6 dB

Performance Control

Channels

4

Sound Color FX

Crush

Dub Echo

Filter

Noise

Sweep

Space

Beat FX

Delay

Echo

Filter

Helix

Phaser

Ping Pong

Pitch

Slip Roll

Spiral

Reverb

Roll

Trans

Vinyl Brake

FX Frequency

Yes

X-PAD

Yes

rekordbox Quantize

Yes

Crossfader

Crossfader Type

Magvel Fader
CURVE Assignable
Yes
Fader Curve
3
Mic
Mic Connection
XLR / 1/4-inch Jack Combo
1/4-inch TRS Jack
Talkover
3 Position Switch
Talkover Attenuator
Yes
Terminals
Inputs
4 Digital (Coaxial)
4 CD/LINE (RCA)
4 PHONO (RCA)
1 AUX (XLR, 1/4 inch TRS Jack)
2 MIC (XLR/TRS Jack Combo, 1/4 inch TRS Jack)
1 Word Clock (BNC)
Send/Return
1 SEND (1/4-inch TS jack)
1 RETURN (1/4-inch TS jack)
LAN
6
USB
2 USB B ports
1 USB A port
Outputs
2 MASTER (XLR, RCA)
1 BOOTH (XLR)
2 HEADPHONE MONITOR (1/4 inch Jack, mini-jack)
1 HEADPHONE MONITOR (1/4 inch Jack)
1 REC (RCA)
1 Digital (XLR)